

Disconnecting Switch

This switch is used in a 1 ϕ 15 kV outdoor power system to isolate the load current transformer magnetizing current and cable charging current for work black-out before isolation and visual inspection of the switch connection status.

Specifications

Type	JK-01-2 1P
Rating voltage (kV)	15
Rating current (A)	600
Short time current 3s kA (rms)	25
Rating frequency (Hz)	50/60
Short peak current kA (peak)	40
AC withstand voltage (kV/min)	50
BIL (kV) 1.2/50 μ s	110

