

CS85

Cloud Speaker Payment Terminal

QR Code Reader + Chip & Tap



Micro & Small Merchants



Fashion & Retail



Food & Beverage



CLOUD SPEAKER



PCI PTS 7.x
SRED



Chip & PIN
Contactless



Dynamic
QR Code



Calculator
App



Long-Lasting
Battery

CS85

Cloud Speaker Payment Terminal

SPECIFICATIONS	CS85-DQR Dynamic QR Code	CS85-SQR Static QR Code	CS85-Mini
 Operating System	Runthos	●	●
 Processor	32-bit ARM CPU	●	●
 Memory	20MB Flash + 3.25MB RAM	●	●
 Card Readers	Chip & PIN Contactless NFC Tag	●	●
 Merchant Display	2.4" Merchant Display (monochrome)	●	●
 QR Display	3.36" QR Display (colour)	QR display plate	N/A
 Amount Display	N/A	2.4" Amount Display (colour)	2.4" Amount Display (colour)
 Camera	N/A	N/A	0.3M Camera
 Comms Configurations	4G + WIFI	4G	4G + WIFI
 Battery	2600mAh 3.6V	●	●
 SIM / SAM	1 Nano SIM 1 eSIM (optional)	●	●
 Keys / Buttons	19 Keys: Power ON/OFF 0~9 8 Function Keys	●	●
 Audio	4Ω, 2W 1 Speaker	●	●
 Ports	1 Type C	●	●
 Environmental	-10°C ~ 50°C (14°F ~ 122°F) Operating Temperature -20°C ~ 70°C (-4°F ~ 158°F) Storage Temperature 5%-96% Relative Humidity, Non-Condensing	●	●
 Certifications	PCI PTS 7.x SRED EMV CL L1 EMV L1 MCL VCPS Expresspay RuPay TQM BIS WPC RoHS	●	●



This document is provided to you for informational purposes only. All features and specifications are subject to change without notice. PAX and the PAX logo are either trademarks or registered trademarks of PAX Technology Limited in China and/or other countries. The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by PAX Technology Limited is under license. Other trademarks and trade names are those of their respective owners. © 2026 PAX Technology Limited. All rights reserved.

